CANTONI MOTOR



MOTOR DATA SHEET

Motor type: **SEh56-2C**

Series: **SINGLE PHASE**

28-03-2024

ELECTRICAL PARAMETERS

U	*CONN.*	*f*	*P*		*Duty*	*I*	*n*	*T*	*TL/T*	*TB/T*	*IL/I*	*Efficiency at load [%]*			*Power factor at load [-]*		
V	-	*Hz*	*kW*	*HP*	-	*A*	*rpm*	*N*	-	-	-	*2/4*	*3/4*	*4/4*	*2/4*	*3/4*	*4/4*
230	-	50	0.18	0.25	S1	1.5	2830	0.61	0.55	1.7	2.8	-	-	60.0	-	-	0.87

GENERAL DATA

Efficiency class	-	Sound pressure level [dB]	-
Frame size	56	Sound power level [dB]	-
Number of poles	2	Terminal box position	top
Starting method	DOL	Possibility of terminal box rotation	yes
Insulation class	F	Bearing on D-side	62012Z
Frequency converter supply	-	Bearing on ND-side	62012Z
Mounting arrangement	IMB3/B5/B35/B14	Bearings regreasing	no
Cooling method	IC411	Housing - material	aluminium
Weight [kg]	3.4	Feet - material	aluminium
Moment of inertia [kgm2]	0.0001	Bearing shields - material	aluminium
Direction of rotation	CW/CCW	Painting	RAL5010
Degree of protection	IP 54/IP 55	Climatic execution	U/2

ENVIRONMENTAL CONDITIONS

Ambient temperature [°C]	from -15 up to +40	Altitude above sea level [m]	up to 1000
Relative humidity [%]	up to 95		

ACCESSORY

Number of terminals or cables	4	Temperature sensors in bearings	no
Cable glands/inlets	1	Winding heaters	no
Temperature sensors in winding	no	Optional accessories	on demand

STANDARDS

IEC 60034-1

CERTIFICATES

on demand

ADDITIONAL INFO

Run capacitor [mikroF/V]	6	Starting capacitor [mikroF/V]	-

As part of our development program, we reserve the rights to alter or amend any of the specifications without giving prior notice.

Copyright © 2024 Cantoni Group www.cantonigroup.com

Cantoni GROUP